

# Motor Gücüne Göre Kontaktör ve Termik Röle Seçim Tablosu

Motor gücüne göre kontaktör ve termik röle seçimi								
380 VOLT MOTOR			DİREKT YOL VERME			YILDIZ ÜÇGEN YOL VERME		
			KONTAKTÖR	TERMİK RÖLE	MANYETİK ŞALTER	KONTAKTÖR		TERMİK RÖLE
kW	A	Cos φ	A	A	A	ÜÇGEN	YILDIZ	
0.06	0.23	0.39	9	0.16-0.25	0.4			
0.09	0.31	0.44	9	0.25-0.40	0.4			
0.12	0.38	0.47	9	0.25-0.40	0.4			
0.18	0.55	0.49	9	0.40-0.63	0.63			
0.25	0.79	0.48	9	0.63-1.00	1			
0.37	1.03	0.54	9	1.00-1.60	1.6			
0.55	1.6	0.52	9	1.60-2.50	1.6			
0.75	2	0.56	9	1.60-2.50	2.5			
1.1	2.6	0.64	9	2,50-4.00	4			
1.5	3.5	0.65	9	2.50-4.00	4	9	9	1.50-2.50
2.2	5	0.66	9	4.00-6.00	6	9	9	2.50-4
3	6.6	0.69	9	5.50-8	8	9	9	2.50-4
3.7	7.7	0.73	9	5.50-8	8	9	9	4-6
4	8.5	0.71	9	7-10	10	9	9	4-6
5.5	11.5	0.72	12	10-13	13	9	9	5.50-8
7.5	15.5	0.73	16	13-18	18	12	9	7-10
11	22	0.75	25	8-25	25	12	9	10-13
15	30	0.75	32	23-32	50	16	9	13-18
18.5	37	0.75	40	30-40	50	16	9	18-25
22	44	0.75	50	38-50	50	32	16	23-32
30	60	0.75	63	57-66	100	50	25	30-40
37	72	0.78	80	63-80	100	80	50	63-80
45	85	0.80	145	75-105	100	145	80	75-105
55	105	0.79	145	95-125	125	145	80	100-160
75	138	0.82	145	100-160	160	185	145	100-160
90	170	0.80	185	125-200	250	185	145	125-200
110	205	0.81	265	200-315	250	265	185	200-315
132	245	0.81	265	200-315	250	265	185	200-315
160	300	0.81	400	250-400	500	400	265	250-400
200	370	0.82	400	315-500	500	400	265	250-400
220	408	0.81	500	315-500	500	500	265	250-400
250	460	0.82	500	400-630	500	500	400	315-500
315	584	0.81	630	400-630		630	400	400-630
335	620	0.82	630	500-800				
400	710	0.85	780	500-800				
500	900	0.84		630-1000				